

Projector Lamps

Code	Volts	Watts	Cap	Ansi Code
A1/215	12	100	GY6.35	FCR
A1/215-HLX	12	100	GY6.35	
A1/216	24	150	G6.35	FCS
A1/216-HLX	24	150	G6.35	
A1/216-300HR	24	150	G6.35	See M184
A1/216-2000HR	24 1	50	G6.35	
A1/218	240	2000	P40s	
A1/220	12	50	G6.35	BRL
A1/220-HLX	12	50	G6.35	
A1/223	24	250	G6.35	EHJ
A1/223-HLX	24	250	G6.35	
A1/225	240	50	B15s	
A1/226	30	375	R7s	DWZ
A1/227	120	420	R7s	FAL
A1/228	120, 240	600	R7s	FCB-120V
A1/229	8	50	GZ6.35	EFM
A1/230	12	75	GZ6.35	EFN
A1/230-HLX	12	75	GZ6.35	
A1/231	12	100	GZ6.35	EFP
A1/231-HLX	12	100	GZ6.35	
A1/232	15	150	GZ6.35	EFR
A1/232-HLX	15	150	GZ6.35	
A1/233	240	650	GY9.5	DYR
A1/234	15	150	G6.35	BRJ
A1/234-HLX	15	150	G6.35	
A1/235	24	250	PG22d	
A1/237	245	500	G6.35	FFX
A1/239	36	400	G6.35	EVD
A1/240	240	300	G17t	
A1/241	240	500	G17t	BCK-120V
A1/242	240	1000	G17t	BRR-120V
A1/244	240	500	GY9.5	
A1/245	240	800	GY9.5	
A1/247	240	650	GY9.5	
A1/248	240	150	G6.35	
A1/249	240	300	G6.35	
A1/250	8	50	2-tab	
A1/252	24	200	GX5.3	EJL
A1/254	240	500	GY9.5	EHA-120V
A1/255	240	800	GY9.5	
A1/256	240	750	G17t	
A1/257	240	650	GY9.5	
A1/258	24	250	GY7.9	EMM
A1/259	24	250	GX5.3	ELC
A1/259-HLX	24	250	GX5.3	
A1/260	12	75	GZ6.35	
A1/261	12	100	GY9.5	FDT

A1/262	24	150	GY9.5	FDS
A1/263	8	50	P30s	
A1/264	120	600	GY9.5	DYS